

Anemometers

Ideal for industrial and home purposes such as measuring wind speed and temperature of CPU, computer fans, air-conditioners, air blowers, etc.



GM816 Hot Wire Anemometer Wind Meter Anemometer / Digital Anemometer

XE-4003-001

Ideal for industrial and home purposes such as measuring wind speed and temperature of CPU, computer fans, air-conditioners, air blowers, etc.

- Measure wind speed and temperature
- The wind speed measuring range is from 0 to 30m/s
- Current and average wind speed measuring
- Maximum and minimum wind speed measuring
- Temperature display in °C/°F
- LCD white backlight display



Anemometer



Accuracy	+/- 5%
Air Temp: Accuracy	+/- 2°C, +/- 3.6F
Air Temp: Range	-10~45°C, 14~113°F
Air Temp: Resolution	Resolution 0.2°C, 0.36°F
Air Velocity: Range	0.3 - 30m/s, 0 - 90km/h, 0 - 5860ft/min, 0 - 65mph, 0 - 55Knots
Air Velocity: Resolution	0.1m/s, 0.3km/h, 19ft/min, 0.2mph, 0.2Knots
Air Velocity: Threshold	0.1m/s, 0.3km/h, 39ft/min, 0.2mph, 0.1Knots
Colour	Yellow / Black
Current Consumption	3mA Approx.
Dimensions	10.5 x 4.5 x 2 cm / (4.13 x 1.77 x 0.79)
Operating Humidity	less than or equal to 90%RH

www.labfacility.com